



Microinverter Datasheet

HMS-1600-4T-NA HMS-1800-4T-NA HMS-2000-4T-NA

Description

Hoymiles new microinverter HMS-2000 series are suitable for high-powered solar panels, which rank among the highest for 4-in-1 microinverters.

Each microinverter can connect up to 4 panels, with independent MPPT and monitoring maximizing the power production of your installation. With a maximum DC voltage of 65 volts, Hoymiles microinverter is a PV Rapid Shutdown Equipment and conforms with NEC-2017 and NEC-2020 Article 690.12 and CEC-2021 Sec 64-218.

The new Sub-1G wireless solution enables more stable communication with Hoymiles gateway DTU.

Features

01	High-powered microinverter for 4-in-1 series with superior performance	04	Independent MPPT and monitoring ensure greater energy harvest and easier maintenance
02	Safer for rooftop solar stations with PV rapid shutdown compliance	05	4-in-1 design enables most cost-effective solar solution
03	With Reactive Power Control, compliant with UL 1741, IEEE 1547, UL 1741 SA, CA Rule21, etc.	06	Sub-1G wireless solution allows stable communication in commercial and industrial settings

Technical Specifications

HMS-1600-4T-NA		HMS-180)0-4T-NA	HMS-2000-4T-NA				
320 to 540+		360 to	600+	400 to 670+				
		65						
		2						
4×12.5		4 × 1	13.3	4 × 14				
4								
1								
1600		18	00	2000				
1440		16	60	1918				
6	6.92	6.92	7.98	7.99	9.22			
240/211-264	208/183-228	240/211-264	208/183-228	240/211-264	208/183-228			
		60/5	5–65					
able) > 0.99 default 0.8 leading0.8 lagging								
< 3%								
4	3	3	3	3	2			
96.70%		96.5	50%	96.50%				
consumption (mW) < 50								
	-40 to +65							
331 × 218 × 36.6								
4.7								
ng Outdoor-IP67 (NEMA6)								
Natural convection-No fans								
munication Sub-1G								
Galvanically Isolated HF Transformer								
hitoring Hoymiles S-Miles Cloud ³								
UL 1741, IEEE 1547, UL 1741 SA, CA Rule21, CSA C22.2 No. 107.1-16 FCC 15B, FCC 15C								
UL	_ 1741, ILLL 134							
	320 to 320 to 4 × 4 × 16 14 6 240/211-264	320 to 540+ 320 to 540+ 4 × 12.5 4 × 12.5 14 14 14 16 6 6.92 240/211-264 208/183-228 3 240/211-264 208/183-228 1 1 1 1 1 1 1 1 1 1 1 1 1	320 to 540+ 360 to 320 to 540+ 360 to 320 to 540+ 360 to 16 16 16 16 16 14× 14×12.5 44× 16 14× 16 6.92 16 6.92 240/211-264 208/183-228 240/211-264 208/183-228 240/211-264 208/183-228 240/211-264 208/183-228 240/211-264 208/183-228 240/211-264 208/183-228 240/211-264 208/183-228 240/211-264 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3	320 to 540+ 360 to 600+ 65 65 16-0 22 4 × 12.5 4 × 13.3 4 × 12.5 4 × 10 4 × 12.5 4 × 10 4 × 12.5 4 × 10 4 × 12.5 4 × 10 4 × 12.5 4 × 10 1 1 1 1 1 1 1 1600	320 to 540+ 360 to 600+ 4400 to 320 to 540+ 360 to 600+ 400 to 65 - - - 165 22 22 - - 164 × 12.5 44 × 13.3 44 × - - 4 × 12.5 44 × 13.3 44 × - - - 14 × 12.5 44 × 13.3 44 × -<			

*1 Nominal voltage/frequency range can vary depending on local requirements. *2 Refer to local requirements for exact number of microinverters per branch. *3 Hoymiles Monitoring System